

ACCTIVA PROFESSIONAL FLASH

/ The professional power supply for diagnosis and software updates



/ The Acctiva Professional Flash supplies the vehicle with current during diagnosis and software updates. 70 A ensures a full charge and startability in just a few minutes. The integral USB interface means the charger is completely future-proof.

PRODUCT INFORMATION

- / Plug & Charge for fully automatic charging.
- / Portable battery charging system with robust, compact housing for a range of uses in the workshop.
- / Edge guard provides stability and protects paint from damage.
- / For charging all lead starter batteries (lead acid, lead calcium, Ca/Ca, lead silver, gel, maintenance-free, EFB, MF, hybrid) and for powering the vehicle.
- / All functions (battery capacity, nominal voltage, service function, EPS/buffering function, I-Check function) can be clearly viewed and set on the display.
- / Up-to-date charging data (charging current, charging voltage, Ah charged so far) is shown on the display.
- / Based on Active Inverter Technology.
- / Integral USB interface allows the charger to be updated.
- / 100% safe for the vehicle, vehicle electronics and battery due to electronic safety, short-circuit protection, electronic reverse polarity protection, safety cut-out and thermal overload protection.

APPLICATIONS

DIAGNOSIS AND FLASHING

- / Supplies parallel loads during diagnosis and software updates. The battery charging system provides the maximum level of safety during this 70 A process.

CHANGING THE BATTERY

- / The back-up mode ensures that user settings in the vehicle are retained while the battery is being changed.

POWER SUPPLY MODE

- / This mode guarantees an external power supply without any support from the battery.

REFRESH MODE

- / This mode regenerates deep-discharge batteries (desulphating).

RAPID CHARGING

- / The powerful device charges the battery fully during short service periods and restores its startability in just a few minutes.

I-CHECK (CURRENT INPUT CHECK)

- / Ten-minute automatic current input check for discharged starter batteries to determine whether the battery is faulty or still functional.

APPLICATION AREAS

/ Vehicle workshop (diagnosis, software updates, showroom, trade fairs, vehicle premieres)



Optional accessories - system case



Optional accessories - wall bracket

ACCTIVA PROFESSIONAL FLASH TECHNICAL DATA

ACCTIVA	PROFESSIONAL FLASH	PROFESSIONAL FLASH UCN	ACCT. PROFESSIONAL 30A UCN
Charging current/boost current	50 / 70 A	50 / 70 A	30 A
Battery capacity	10 - 250 Ah	10 - 250 Ah	10 - 300 Ah
Battery voltage	12 V		
Mains voltage +/- 15 %	230 V (50/60 Hz)	115 V (50/60 Hz)	115 V (50/60 Hz)
Charging characteristic	IUoU		
Degree of protection	IP 20		
Dimensions (L x W x H)	315 x 110 x 200 mm		
Weight	5.7 kg		
Mark of conformity	CE, NSW (Australia)	cTÜVus (Canada/USA)	cTÜVus (Canada/USA)
Mains fuse	Europe: 16 A / Australia: 10 A	US/CAN: 15 A	US/CAN: 15 A
EMC emission class	A	FCC15 Class A	A

Information about options available on request.

/ Perfect Welding / Solar Energy / Perfect Charging

THREE BUSINESS UNITS, ONE GOAL: TO SET THE STANDARD THROUGH TECHNOLOGICAL ADVANCEMENT.

What began in 1945 as a one-man operation now sets technological standards in the fields of welding technology, photovoltaics and battery charging. Today, the company has around 5,660 employees worldwide and 1,321 patents for product development show the innovative spirit within the company. Sustainable development means for us to implement environmentally relevant and social aspects equally with economic factors. Our goal has remained constant throughout: to be the innovation leader.

Further information about all Fronius products and our global sales partners and representatives can be found at www.fronius.com

Fronius India Private Limited
Plot no BG-71/2/B,
Pimpri Industrial Area,
MIDC- Bhosari,
Pune- 411026, India
Telephone +91 98 20 60 52 97
perfect.charging.in@fronius.com
www.fronius.in

Fronius UK Limited
Maidstone Road, Kingston
Milton Keynes, MK10 0BD
United Kingdom
Telephone +44 1908 512 300
Fax +44 1908 512 329
charger.sales.uk@fronius.com
www.fronius.co.uk

Fronius USA LLC
6797 Fronius Drive
Portage, IN 46368
USA
Telephone +1 219-734-5500
Fax +1 219-734-5502
perfect.charging.us@fronius.com
www.fronius.us

Fronius International GmbH
Froniusplatz 1
4600 Wels
Austria
Tel +43 7242 241 3000
Fax: +43 7242 241-952560
perfect.charging@fronius.com
www.fronius.com